

Sydney

Two-Way RF4CE Touchpad Remote Control

ENHANCE THE HOPPER EXPERIENCE with Sydney, the innovative touchpad remote control with voice recognition that provides the most user-friendly experience with the Hopper® or Hopper with Sling®.

Features

- Streamlined remote—19 buttons on top, 7 total on the sides—for full TV, receiver and DVR support
- Attractive, small ergonomical design with chrome highlights and red striping
- Large, easy-to-see buttons
- Clickable touchpad allows for smooth navigation and responds to swipe, scroll and pinch-zoom gestures
- New intuitive user interface minimizes the need to look at the remote during operation, offering improved navigation
- Dynamic backlit touchpad automatically illuminates the numeric keypad when needed (e.g., channel change, password entry, etc.) and otherwise remains invisible
- Advanced voice recognition via an internal microphone gives viewers the ability to quickly and easily search for shows and browse content
- The Locate Remote feature helps discover a lost remote using audible tones and flashing lights
- Backlight for all buttons in low light conditions
- Dedicated hotkey for user's favorite function
- Fast access to on-screen help prompts and tips
- New Options button to access settings in context without the need to navigate multiple menus
- Easily pair and unpair the remote to the receiver with the touch of a button
- Simple on-screen setup and device programming
- Controls up to two IR devices (TV/AUX modes); can control more devices with IR learning
- IR learning captures and reproduces device codes from an original manufacturer's remote control
- The Link Quality Indicator helps maximize signal strength between the remote and receiver
- Limited Mode prevents the viewer from accidentally changing the TV's input
- Excellent power management and battery life
- Battery voltage monitor for alerting the user when the batteries are low
- Flash memory for firmware updates and receiver settings storage
- Automatically receives over-the-air firmware updates





Technical Specifications

Topside Features

TV and Receiver Buttons: 19

LED Mode Indicators: SAT, TV, AUX

Microphone

Clickable touchpad with dynamically illuminated numeric keypad

Side Features

Left-Side Buttons: SAT, TV, AUX, Input

Right-Side Buttons: Mic, Hotkey, Backlight

Mechanical Features

Intuitive button layout

Textured black ABS plastic

Backlit metal-dome buttons

IR lens cover

Chrome symbols and red striping

Dimensions

Height x Width x Depth: 5.59” x 2.25” x 1.02”

IR Database

Resides on the set-top box. The remote downloads individual CE equipment codesets via the RF link using the EchoStar ELCC format.

Power Supply

2 AA batteries

Regulatory

FCC Compliance

Packaging Options

Bulk and individual kit configurations available

